EXPLORER 540 LTE Modem

Turn your BGAN into a dual mode M2M terminal

June 2017 Draft Product Sheet

The most important thing we build is trust





EXPLORER 540 LTE Modem

Turn your BGAN into a dual mode M2M terminal

- Powerful LTE Modem designed for the EXPLORER 540 BGAN M2M
- Simply connect the LTE Modem on the back of the EXPLORER 540 via USB and use a local cellular network as an alternative to BGAN
- Automatic failover between BGAN and cellular networks
- Designed for harsh environments with IP66 and an extended temperature range.
- Highest throughput of up to 150 Mbps with LTE Cat. 4





Features

LTE: 150 Mbps DL, 50 Mbps UL (Cat. 4)

Channel Bandwidths: 1.4 - 20 Mhz

MIMO 2x2

UMTS/DC-HSPA+: 42 Mbps downlink, 5.76 Mbps uplink

GSM: GPRS & EDGE Class 12

Model	LTE module	Region	Access Technology		
			LTE Bands	UMTS Bands	GSM Bands
403715A-101	ublox TOBY-L200	North America	2,4*,5,7	850/900/AWS/ 1900/2100	850/900/ 1800/1900
403715A-102	ublox TOBY-L210	EUROPE / APAC	1,3*,5,7,8,20	850/900/ 1900/2100	850/900/ 1800/1900
*Requires external housing					

Antenna: Integrated cellular antenna

Dimensions:

L/W/D: 85 / 85 / 40 mm

Weight: 380g

Environmental:

Operating Temperature: -40 to +85°C (extended range)

Industrial Grade: Automotive

Ingress Protection: IP66

BGAN firmware:

EXPLORER 540 version 1.02 or later

Product numbers:

403715A-101: EXPLORER 540 LTE Modem (North America) 403715A-102: EXPLORER 540 LTE Modem (Europe / APAC)

403715A-110: LTE Modem Extension Kit

- To mount the LTE Modem separate from EXPLORER 540

Availability:

The US version (-101) and the Europe / APAC version (-102), as well as the Extension Kit, are scheduled to ship in July.

Cellular SIM Card Holder Micro USB Connector Short cable included





Optional LTE Modem Extension Kit for external housing

For further information please contact:

Cobham SATCOM Lundtoftegaardsvej 93 D DK-2800 Kgs. Lyngby Denmark

Tel: +45 3955 8800 Fax: +45 3955 8888